



Basics of operating the System:

You must have a ready green light before arming. If not press * to see zone numbers which are open or in alarm status.

Leaving Home? Press # and "2" (away)

This will activate the motion and doors and allows a normal entrance delay on doors when coming home

Staying Home or expecting someone to return home? Press # and "3" (stay)

This bypasses motion and activates the doors and allows a normal entrance delay on the doors for whoever is coming home.

Bedtime? Press # and "7" (instant)

This bypasses motion and activates the doors with NO entrance DELAY

Disarm System: enter 4 digit code "1" (off)

ALARM (Siren) enter 4 digit code and "1" (off) Two times

First time turns the siren off and second time resets the keypad then call monitoring center and give them your password.

Duress Situation (being forced to disarm your system)

enter your 4 digit Duress code and "1" (off)

How to change your current code

Master Code: 1234

Change Code: 1234 8 0 2 new code twice

Example: 1234 8 0 2 4321 4321 for additional codes master code 8 0 3 4 digit code once
Then 8 0 4, 8 0 5, and so on to 8 3 1